FORMULA'S:
Mirrored Wardrobe Doors
21S - BiPass

			Example: 1	Example: 2
Net Finished Heights:	80 1/2"			
	96"	Over All Height	80 1/2"	96"
			- 2 5/8"	- 2 5/8"
Mirror Height		Mirror Height	77 7/8"	93 3/8"
Total Height minus:	- 2 5/8"		+ 1/8"	+ 1/8"
		Stile Length	78"	93 1/2"
Stile Length				
Mirror Height plus:	+ 1/8"			
		Over All Width	59"	118"
Mirror Width			+ 1"	+ 2"
Total Width Plus:	+1" Per Overlap*		60"	120"
	Divide by # of		/2	/3
	Panels	Mirror Width	30"	40"
Rail Length			- 1 1/2"	- 1 1/2"
Mirror Width minus:	- 1 1/2"	Rail Length	28 1/2"	38 1/2"

* Overlap is # of Panels minus 1