

## FORMULA'S: Mirrored Wardrobe Doors 28A - BiPass

Net Finished	80 1/2"		Example: 1	Example: 2
Heights:	96"	Over All Height	80 1/2"	96"
			- 2 5/8"	- 2 5/8"
Mirror Height		Mirror Height	77 7/8"	93 3/8"
Total Height minus:	- 2 5/8"		+ 1/4"	+ 1/4"
		Stile Length	78 1/8"	93 5/8"
Stile Length				
Mirror Height plus:	+ 1/4"	Over All Width	59"	142 5/8"
			+ 1 1/4"	+ 2 1/2"
Door Width			60 1/4"	145 1/8"
Total Width:	+ 1 1/4" Per Overlap*		/2	/3
	Divide by # of Panels	Door Width	30 1/8"	48 3/8"
Mirror Width			- 1 1/2"	- 1 1/2"
Total Width minus:	- 1 1/2"	Mirror Width	28 5/8"	46 7/8"
			- 1"	- 1"
Rail Length		Rail Length	27 5/8"	45 7/8"
Mirror Width minus:	- 1"			

\* Overlap is # of Panels minus 1

\* Regarding width Calculations....Overlap is Manufactures recommendation, however, more overlap is per Customer Discretion.